

1 ft Coax HD15 VGA to 5 BNC RGBHV Monitor Cable - M/F

Product ID: VGABNCMF1



The VGABNCMF1 1-foot Coax HD15 VGA to 5 BNC RGBHV Adapter Cable features an HD15 VGA (male) connector and 5 BNC (RGBHV) (female) connectors, allowing you to connect your existing BNC video source to a VGA distribution amplifier or PC.

The cable can also be used with a VGA out signal, breaking out to 5 BNC female connectors that can be used with a 5 BNC (M-M) cable for use with a BNC monitor/display.

Certifications, Reports and Compatibility

Applications

Connect your BNC connected cabled panels and projectors to a VGA distribution amplifier or PC

Features

- Short flexible cable design
- HD15 VGA Male to 5 BNC Female Connectors

ш.	arc	J		_
м	arc	ıw	aг	Р

Warranty Lifetime

Connector Plating Nickel

Cable Jacket Material PVC - Polyvinyl Chloride



	Fire Rating	CMG Rated (General Purpose)	
Connector(s)	Connector A Connector B	VGA (15 pin, High Density D-Sub) BNC (RF Coax)	
Special Notes / Requirements	Note	RGB signal: Red, Green, Blue wires, Vertical Sync: Black wire, Horizontal Sync: White wire	
Physical Characteristics	Color	Black	
	Wire Gauge Cable Length	28 AWG 12.0 in [30.5 cm]	
	Cable OD Product Length	0.3 in [8.5 mm] 12.0 in [30.5 cm]	
	Product Width Product Height	1.3 in [33.0 mm] 0.6 in [15.0 mm]	
	Weight of Product	3.6 oz [103.0 g]	
Information	Package Length	8.9 in [22.5 cm]	
	Package Width	4.9 in [12.5 cm]	
	Package Height Shipping (Package) Weight	0.7 in [17.0 mm] 3.8 oz [108.0 g]	
What's in the Box	Included in Package	1 ft Coax HD15 VGA to 5 BNC RGBHV Monitor Cable - M/F	

^{*}Product appearance and specifications are subject to change without notice.